



■ Features :

- Universal AC input / Full range
- Built-in active PFC function
- High efficiency up to 93%
- Withstand 300VAC surge input for 5 seconds
- Protections: Short circuit / Overload / Over voltage / Over temperature
- Built-in 12V/0.5A auxiliary output
- 5"x3" compact size
- Free air convection for 200W and 300W with 20.5 CFM forced air
- With power good and fail signal output
- Built-in remote sense function
- No load power consumption under 0.5W by PS-ON control
- Standby 5V@1A with fan, @ 0.6A without fan
- 3 years warranty







SPECIFICATION

MODEL		EPP-300-12	EPP-300-15	EPP-300-24	EPP-300-27	EPP-300-48	
	DC VOLTAGE	12V	15V	24V	27V	48V	
OUTPUT	RATED CURRENT (20.5CFM)	25A	20A	12.5A	11.12A	6.25A	
	CURRENT RANGE (convection)	0 ~ 16.67A	0 ~ 13.33A	0 ~ 8.33A	0~7.4A	0 ~ 4.17A	
	CURRENT RANGE (20.5CFM)	0 ~ 25A	0 ~ 20A	0 ~ 12.5A	0 ~ 11.12A	0 ~ 6.25A	
	RATED POWER (convection)	200W	200W	199.9W	199.8W	200.2W	
	RATED POWER (20.5CFM)	300W	300W	300W	300.24W	300W	
	RIPPLE & NOISE (max.) Note.2	120mVp-p	120mVp-p	150mVp-p	200mVp-p	250mVp-p	
	VOLTAGE ADJ. RANGE	Main output:11.4 ~ 12.6V	Main output:14.25 ~ 15.75V	Main output:22.8 ~ 25.2V	Main output:25.65 ~ 28.35V	Main output:45.6 ~ 50.4	
	VOLTAGE TOLERANCE Note.3	±3.0%	±3.0%	±2.0%	±2.0%	±2.0%	
	LINE REGULATION	±0.5%	±0.5%	±0.5%	±0.5%	±0.5%	
	LOAD REGULATION	±1.0%	±1.0%	±1.0%	±1.0%	±1.0%	
	SETUP, RISE TIME	2500ms, 30ms/230VAC 3000ms, 30ms/115VAC at full load					
	HOLD UP TIME (Typ.)	13ms/230VAC/115VAC at full load					
INPUT	VOLTAGE RANGE Note.5	90 ~ 264VAC 127 ~ 370VDC					
	FREQUENCY RANGE	47 ~ 63Hz					
	POWER FACTOR (Typ.)	PF>0.93/230VAC					
	EFFICIENCY (Typ.)	90%	90%	92.5%	93%	93%	
	AC CURRENT (Typ.)	3.5A/115VAC 1.8A/2	230VAC				
	INRUSH CURRENT (Typ.)	COLD START 40A/115VAC 80A/230VAC					
	LEAKAGE CURRENT	<2mA/240VAC					
PROTECTION	OVERLOAD	105 ~ 135% rated output power					
				lly after fault condition is re	emoved		
	OVER VOLTAGE	13.5 ~ 15V	16.2 ~ 18.5V	26 ~ 30V	29.5 ~ 33.5V	52 ~ 59.5V	
		Protection type: Shut down o/p voltage, re-power on to recover					
		110°C±5°C (TSW1) detect on heatsink of power transistor					
	OVER TEMPERATURE	$115\pm5^{\circ}$ C (12V,15V),85 $\pm5^{\circ}$ C (24V,27V,48V) (TSW2) detect on heatsink of output diode					
		Protection type: (TSW1)Shut down o/p voltage, recovers automatically after temperature goes down					
		Protection type : (TSW2)Shut down o/p voltage, re-power on to recover					
FUNCTION	5V STANDBY	5VSB: 5V@0.6A without fan, 1A with fan 20.5CFM; tolerance ± 2%, ripple: 150mVp-p(max.)					
	AUXILIARY POWER (AUX)	12V@0.5A for driving a fan ; tolerance -15% ~ +10%					
	PS-ON INPUT SIGNAL	Power on: PS-ON = "Hi" or " > 2 ~ 5V"; Power off: PS-ON = "Low" or " < 0 ~ 0.5V"					
	POWER GOOD / POWER FAIL	500ms>PG>10ms; The TTL signal goes high with 10ms to 500ms delay after power set up; The TTL signal goes low at least 1ms before Vo below 90% of rated value					
ENVIRONMENT	WORKING TEMP.	-30 ~ +70°C (Refer to "Derating Curve")					
	WORKING HUMIDITY	20 ~ 90% RH non-condensing					
	STORAGE TEMP., HUMIDITY	-40 ~ +85°C , 10 ~ 95% RH					
	TEMP. COEFFICIENT	±0.03%°C (0~50°C)					
	VIBRATION	10 ~ 500Hz, 2G 10min./1cycle, 60min. each along X, Y, Z axes					
	SAFETY STANDARDS	UL60950-1, TUV EN60950-1 approved					
SAFETY &	WITHSTAND VOLTAGE	I/P-O/P:3KVAC I/P-FG:2KVAC O/P-FG:0.5KVAC					
EMC	ISOLATION RESISTANCE	I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C / 70% RH					
(Note 4)	EMC EMISSION	Compliance to EN55011 (CISPR11), EN55032 (CISPR32), Conduction Class B, Radiation Class B; EN61000-3-2,3;					
	EMC IMMUNITY	Compliance to EN61000-4-2,3,4,5,6,8,11, EN55024, EN60601-1-2, criteria A					
OTHERS	MTBF	160Khrs min. MIL-HDBK-217F (25°C)					
	DIMENSION	127*76.2*35mm (L*W*H)					
	PACKING	0.37 Kg; 36pcs/14.3Kg/1.03CUFT;					
NOTE	Ripple & noise are measure Tolerance : includes set up The power supply is consid EMC directives. For guidan (as available on http://www. Derating may be needed ur	parameters NOT specially mentioned are measured at 230VAC input, rated load and 25°C of ambient temperature. pple & noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 47uf parallel capacitor. lerance: includes set up tolerance, line regulation and load regulation. e power supply is considered a component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets ### C directives. For guidance on how to perform these EMC tests, please refer to "EMI testing of component power supplies." is available on http://www.meanwell.com) rating may be needed under low input voltages. Please check the derating curve for more details. at Sink HS1,HS2 can not be shorted.					



